

## RetroSound® Laguna Radio

---



The RetroSound® Laguna looks like your original radio while offering the most modern technologies for your classic. Laguna features authentic push-button styling and an AM/FM tuner with 30 pre-sets. A rear-mounted auxiliary input is included to play portable devices such as iPod® or portable satellite radio. A built-in 18 watts x 4 channel RMS amplifier provided plenty of power to your speakers. Laguna features our patented InfiniMount adjustable shaft system to make installation easy in virtually any classic vehicle.

**To find the Laguna for your vehicle, use the year, make and model search at the top left of this page.**

- Authentic push-button styling
- AM/FM tuner with 30 pre-sets
- Auxiliary input for portable devices
- 18 watts x 4 channel RMS power amplifier
- Patented InfiniMount adjustable shaft system
- Body can be mounted remotely for custom installation using optional extension cable
- Power antenna lead and amp turn on lead included
- The pictured **GM logo screen protector** is available separately.

Laguna is available in chrome or black.



## SPECIFICATIONS

### FM

Tuning Range (USA, EUR, AUS, JAP, RUS tuning capable) with RDS	87.5-107.9MHz
Antenna Terminal	External Antenna Connector
Usable Sensitivity	12.5 dBf
Selectivity	75 dB @ 400kHz
Signal to Noise Ratio	62 dB (Stereo), 67 dB (mono)
Harmonic Distortion @ 1 kHz	0.8% (stereo), 0.5% (mono)
Separation	32 dB @ 1kHz
Frequency Response	30-16,000 Hz

### AM (EU and US Tuning Capable)

Tuning Range (USA, EUR, AUS, JAP, RUS tuning capable)	530-1710 kHz
Antenna Terminal	External Antenna Connector

### General

Dimensions (radio face & push-buttons only)	3.5"W x 1.5" H x 1.05" D
Dimensions (radio body)	3.96"W x 1.98"H x 4.30"D
Power Requirements	11.5-14.4 volts
Current Consumption (during operation)	Max. 15A
Current Consumption (car off)	<3.5 mA
Output Power (@ 14.4 volts @ 4 ohm @ 1% THD)	18x4 watts RMS 40x4 Max Power
Output Impedance	4-8ohm
AUX Input (AUX cable length, 8")	>300 mV / 6 kΩ