

RetroSound® Laguna Radio



The RetroSound® Laguna looks like your original radio while offering the most modern technologies for your classic. Laguna features authentic push-button styling and an AM/FM tuner with 30 pre-sets. A rear-mounted auxiliary input is included to play portable devices such as iPod® or portable satellite radio. A built-in 18 watts x 4 channel RMS amplifier provided plenty of power to your speakers. Laguna features our patented InfiniMount adjustable shaft system to make installation easy in virtually any classic vehicle.

To find the Laguna for your vehicle, use the year, make and model search at the top left of this page.

- Authentic push-button styling
- AM/FM tuner with 30 pre-sets
- Auxiliary input for portable devices
- 18 watts x 4 channel RMS power amplifier
- Patented InfiniMount adjustable shaft system
- Body can be mounted remotely for custom installation using optional extension cable
- Power antenna lead and amp turn on lead included
- The pictured **GM logo screen protector** is available separately.

Laguna is available in chrome or black.



SPECIFICATIONS

FM

Tuning Range (USA, EUR, AUS, JAP, RUS tuning capable) with RDS	87.5-107.9MHz
Antenna Terminal	External Antenna Connector
Usable Sensitivity	12.5 dBf
Selectivity	75 dB @ 400kHz
Signal to Noise Ratio	62 dB (Stereo), 67 dB (mono)
Harmonic Distortion @ 1 kHz	0.8% (stereo), 0.5% (mono)
Separation	32 dB @ 1kHz
Frequency Response	30-16,000 Hz

AM (EU and US Tuning Capable)

Tuning Range (USA, EUR, AUS, JAP, RUS tuning capable)	530-1710 kHz
Antenna Terminal	External Antenna Connector

General

Dimensions (radio face & push-buttons only)	3.5"W x 1.5" H x 1.05" D
Dimensions (radio body)	3.96"W x 1.98"H x 4.30"D
Power Requirements	11.5-14.4 volts
Current Consumption (during operation)	Max. 15A
Current Consumption (car off)	<3.5 mA
Output Power (@ 14.4 volts @ 4 ohm @ 1% THD)	18x4 watts RMS 40x4 Max Power
Output Impedance	4-8ohm
AUX Input (AUX cable length, 8")	>300 mV / 6 kΩ